

Voltage U (V)	Current I (A)	Input (W)	Speed (RPM)	Torque (Ncm)	Output (W)	Efficiency (%)
24,00	12,00	288,0	32100	6,0	201,7	70,0
24,00	15,80	379,2	27300	10,0	285,9	75,4
24,00	18,40	441,6	25270	13,0	344,0	77,9
24,00	20,20	484,8	24200	15,0	380,1	78,4
24,00	22,70	544,8	22830	18,0	430,3	79,0
24,00	24,40	585,6	22030	20,0	461,4	78,8
24,00	27,80	667,2	20650	24,0	519,0	77,8
24,00	31,20	748,8	19450	28,0	570,3	76,2
24,00	35,70	856,8	18300	33,0	632,4	73,8
24,00	38,50	924,0	17650	36,0	665,4	72,0

