

Voltage U (V)	Current I (A)	Input (W)	Speed (RPM)	Torque (Ncm)	Output (W)	Efficiency (%)
13,50	8,70	117,5	32000	1,8	60,3	51,4
13,50	13,40	180,9	23500	5,0	123,0	68,0
13,50	17,50	236,3	19800	8,0	165,9	70,2
13,50	20,00	270,0	18200	10,0	190,6	70,6
13,50	23,40	315,9	16500	13,0	224,6	71,1
13,50	25,50	344,3	15600	15,0	245,0	71,2
13,50	30,30	409,1	13900	20,0	291,1	71,2
13,50	36,00	486,0	12800	25,0	335,1	69,0
13,50	42,00	567,0	11800	30,0	370,7	65,4
13,50	48,50	654,8	11000	35,0	403,2	61,6

