

Voltage U (V)	Current I (A)	Input (W)	Speed (RPM)	Torque (Ncm)	Output (W)	Efficiency (%)
13,00	11,0	143,0	18000	1,5	28,3	19,8
13,00	18,9	245,7	10550	15,0	165,7	67,4
13,00	25,4	330,2	7880	30,0	247,6	75,0
13,00	34,0	442,0	6571	50,0	344,1	77,8
13,00	42,3	549,9	5884	70,0	431,3	78,4
13,00	50,2	652,6	5420	90,0	510,8	78,3
13,00	54,0	702,0	5229	100,0	547,6	78,0
13,00	58,3	757,9	5050	110,0	581,7	76,8
13,00	67,0	871,0	4765	130,0	648,7	74,5
13,00	76,3	991,9	4496	150,0	706,2	71,2

