

Voltage U (V)	Current I (A)	Input (W)	Speed (RPM)	Torque (Ncm)	Output (W)	Efficiency (%)
42,10	2,70	113,7	18000	1,4	26,4	23,2
42,10	3,00	126,3	15180	5,0	79,5	62,9
42,09	4,00	168,4	11760	10,0	123,2	73,1
42,08	5,50	231,4	8800	20,0	184,3	79,6
42,05	8,30	349,0	6762	40,0	283,2	81,2
42,00	11,00	462,0	5865	60,0	368,5	79,8
42,00	13,90	583,8	5275	80,0	441,9	75,7
42,00	17,20	722,4	4850	100,0	507,9	70,3
42,00	23,00	966,0	4340	130,0	590,8	61,2
42,00	32,00	1344,0	4020	158,0	665,1	49,5

General purpose motor measured @ 13, 24, and 42V, see Tab. 1, 2, 3.

